

Case 99-CS003/US

**\*METHOD AND ARRANGEMENT FOR ESTABLISHING A  
CONNECTION BETWEEN SATELLITES\***

**Applicant:**

Contraves Space AG  
Schaffhauserstrasse 580  
8052 Zürich  
Switzerland

**Inventors:**

Dr. Edgar FISCHER  
Hägglweg 6  
CH-8555 Müllheim Dorf TG

Nationality:  
Swiss

Andreas MÄRKI  
Haldenstrasse 16  
CH-8703 Erlenbach ZH

Nationality:  
Swiss

Both inventors are employees of Contraves Space AG

**Priority:**

Switzerland, Nr. 1999 2357/99

**Filing Date:**

December 22, 1999

**Contraves Space AG**  
Schaffhauserstrasse 580, 8052 Zürich, Switzerland

Case 00-CS003/US

U S A

20

## METHOD AND ARRANGEMENT FOR ESTABLISHING A CONNECTION BETWEEN SATELLITES

## FIELD OF THE INVENTION

The invention relates to a method and an arrangement for establishing a connection between a receiver and a transmitter, located at a distance from the former, by means of lightwaves, which carry data signals and beacon light, wherein an acquisition receiver for acquiring the lightwaves is provided in the receiver, which generates acquisition sensor signals from the received lightwaves.

## BACKGROUND OF THE INVENTION

Sometimes a "wide angle camera", in cooperation with a so-called beacon laser is used to determine the alignment data for establishing an optical communications connection between two satellites. To avoid more complex, and therefore more interference-prone, search algorithms, the camera is usually laid out in such a way that it

can cover the entire uncertainty cone, which is created by the uncertainty of the position of the own and the opposite stations, as well as the uncertainty regarding tilting in the inertial systems of both stations. Because of the uncertainty cone, the camera must cover an angular area of approximately  $\pm 0.5^\circ$ . However, at the same time the natural beam divergence of the communications beam being used comprises only a few micro-radians. This condition requires an extremely wide dynamic range of the ratio of visual angle / producible angular resolution. In addition, alignment errors between the optical device of the wide angle camera and the optical search device of the communications beam also have aggravating results. The transmission beam will move in a random manner within a defined solid angle area because of certain natural mechanical effects. Based on the limited resolution of the wide angle camera which can be achieved, as well as its limited electrical bandwidth, there is therefore a high degree of probability that the communications beam illuminates the opposite station only rarely. Thus, the opposite station is not provided the opportunity of becoming aligned with the received communications beam and in this way to initiate higher frequency "tracking" with a high degree of angular resolution. In the normal case, tracking of the opposite station in the communications mode takes place with the aid of the received communications light. Sensors with high spatial and/or electrical resolution are employed to obtain the spatial deviation signals (tracking signals).

For checking the optical alignment of two light sources in the course of coherent heterodyne reception, an arrangement is furthermore known from **EP 0 831 604 A1**, having a local laser and two detectors, each of which comprises two identical detector halves, which are respectively separated by a strip-shaped interruption, or gaps, in the photo diode electrode face between the adjoining halves, wherein the gaps of the two detectors are arranged orthogonally in respect to each other. This arrangement is used as a direction-selective optical monomode receiver. Here, an obscuration is provided in a receiving telescope of this arrangement, as well as in the beam path of the local laser. This makes it possible to generate an error signal for a spatial beam regulation of an optical heterodyne receiver, while preventing systematic losses and at the same time only minimally interfering with the data signal to be transmitted, along with a good signal-to-noise ratio.

Finally, an optical bench is known from **EP 0 844 473 A1**, whose bench structure is designed in such a way that, in case of a heat dilation of arms provided for connecting the receiving elements of various optical units, these receiving elements can be displaced without tilting transversely in respect to axes which assume defined angular positions in respect to each other and in relation to the bench structure. Such an optical bench can be combined with the arrangement mentioned at the outset.

Although such "tracking sensor" methods permit simultaneous communications and the determination of the spatial tracking error, the respective arrangements have been

shown to be disadvantageous because of the relatively large adjustment outlay, in particular in the course of their manufacture.

## OBJECT AND SUMMARY OF THE INVENTION

It is therefore the object of the invention to provide a method and an arrangement for establishing a connection between satellites in an acquisition phase, which results in a simpler adjustment of such a system.

This object is attained in an advantageous manner in accordance with the invention by means of a method in accordance with claim 1 and an arrangement in accordance with claim 4.

The structural outlay for the creation of such systems can be significantly reduced by means of the invention, which in the end leads to reduced demands made on complexity, electrical output requirements and mass.

Other advantageous embodiments of the invention ensue from the further dependent claims.

The invention will be explained in greater detail in what follows by way of example, making reference to the drawings.

## BRIEF DESCRIPTION OF THE DRAWINGS

**Fig. 1** is a schematic block diagram of an arrangement in accordance with the invention,

**Fig. 2** is a schematic representation of the movement of a light spot on the front of a lightwave fiber,

**Fig. 3** is a schematic diagram of the chronologically asymmetric intensity signal on the detectors, if the fiber axis does not rotate concentrically around the optical axis of the opto-mechanical system, and

**Fig. 4** is a simplified representation of a device for calibrating the deviation from its nominal position of a receiving beam in a terminal.

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Similar to the arrangement known from the mentioned **EP 0 831 604 A1**, in accordance with **Fig. 1** an **Rx-wave** or information lightwave **1** is received by means of a receiving unit consisting of a receiver telescope **2**, a fine alignment mechanism **3** and a lens **4**. The wave **1** also contains beacon light, which arrives not tightly bundled, but at a

relatively wide angle.

In contrast to the mentioned arrangement, in accordance with the present invention the received wave **1** is fed via a fiber nutator **5** to an optical waveguide coupler **6**. An end of a polarization-maintaining monomode fiber **7** can be connected to the fiber nutator **5** for conducting the beams received over the optical receiver unit to the optical waveguide coupler **6**, and via further monomode fibers **8** and **9** to respectively one detector **10** or **11**. However, in accordance with the present invention, the beams received via the optical receiver unit are preferably conducted over a chromatic diplexer **51** and a monomode fiber **52** for data light to the optical waveguide coupler **6**. Such a fiber nutator **5** is essentially a deflecting unit with a fiber which is driven to nutate, for example by means of a piezo-mechanism. A further, preferably polarization-maintaining fiber **13** is connected to a local laser **12** for conducting the beams generated by the local laser **12** to the optical waveguide coupler **6**, and then via the monomode fibers **8** and **9** to the two detectors **10** or **11**. The detectors **10** and **11** need to be split, as in the known arrangement. The deflecting unit **5** can receive control signals  $S_p$  from a control device **14** via a bus or lines. The optical waveguide coupler **6** preferably is a 50%-to-50% coupler. By means of a polarization-maintaining fiber coupler it is possible to achieve a fiber coupler which is simple and simultaneously inherently stable over a long time.

In place of the mechanical fiber nutator as the deflecting unit it is also possible to employ an electro-optical deflector, wherein an electrical voltage creates a linear electrical field gradient via the aperture of an electro-optical crystal. An aperture of approximately 1 mm is easily achievable even with such a deflector.

The detectors **10** and **11** deliver signals **Sa** or **Sb** via respective amplifiers **15** or **16**, which are employed as the useful signals. The low-frequency portion of these signals **Sa** and **Sb** are also supplied to the differential inputs of a differential amplifier **17**. The arrangement of the invention additionally comprises a sensor **53**, which is connected with the output of the diplexer **51** via a fiber **64**, preferably a monomode fiber, as well as two discriminators **56**, **57**, a higher order system control **58** and a CPA (coarse pointing assembly) unit **174**. The sensor or detector **53**, which is faster than the acquisition sensor **171**, can be a photodiode, for example. The input sides of the discriminators **56** and **57**, which can be synchronous modulators and amplifiers, are respectively connected with an output of the sensor **63** or of the amplifier **17**. A reflecting surface **R4**, which acts as a beam splitter, is also provided in the fine alignment mechanism **3** for deflecting the beams which, via a focusing installation **FA**, which is preferably fixed in place, then reaches an acquisition sensor **AS 171** such is provided anyway in arrangements of this type, but in another form. The sensor **171** is a large-surfaced matrix sensor with a surface of  $6 \times 8 \text{ mm}^2$ , for example, which is scanned and therefore is slow. The system control **58** is provided on the input side with output signals  $S_c$ ,  $S_m$  and  $S_n$  from the sensor **171** or from the discriminators **56**, **57**.

The system control **58** has various outputs for delivering signals via lines **191**, **192**, **193** to respectively one CPA unit **174**, an electronic control device FPA (fine pointing assembly) **175**, or a PAA (point-ahead assembly) unit, and in addition it is bidirectionally connected with the control unit **14**, which is also called deflector selection. To this end the receiver telescope **2** is controlled by an output signal **Sg** of the CPA unit **174**, the fine alignment mechanism **3** by a control signal **Sf** from the unit **175**, and the lens **4**, the deflecting unit **5** and the discriminators **56**, **57** by signals **So**, **Sp** or **St** (Fig. 1). The signals **Sp** and **St** are quadrature signals ( $\sin \omega t$ ,  $\cos \omega t$ ), such as are used for creating Lissajous' figures.

Fig. 2 shows how a light spot **22**, guided by this controlled movement **21**, is projected on a diametrical surface at the end of the lightwave fiber of the deflecting unit **5**. The light spot **22** can be brought at least approximately up to the center of the lightwave fiber by means of the control.

Fig. 3 shows how the mean intensity signal **31** on the detectors **10** and **11** has an overlaid modulation signal **32** if scanning by the fiber axis is not performed concentrically around the optical axis of the opto-mechanical system. The task of the system control **58** lies in moving the fine alignment mechanism **3**, the end of the fiber **7** and/or the lens **4** in such a way, that this modulation signal **32** reaches a minimum value or a zero value.

As can be seen in Fig. 4, one terminal can be provided for three channels, namely for a transmitting channel **Tx**, for a receiving channel **Rx1** with a fiber nutator **5** (Figs. 1 and 4), which is considered to be the receiving sensor **RS1**, and for an acquisition channel **Ax** with an acquisition sensor **AS 171** (Figs. 4 and 1).

In accordance with Fig. 4, a collimator device **KTX**, a first reflecting surface **R1**, a second reflecting surface **R2**, a third reflecting surface **R3**, a fourth reflecting surface **R4**, a fifth reflecting surface **R5** and a quarter-wave plate **QWP1** are arranged in the transmitting channel **Tx**, viewed in the beam direction. The first reflecting surface **R1** is a component of a point-ahead assembly **PAA**. The second reflecting surface **R2** is a component of a polarizing beam splitter **PBS**, which is embodied in such a way that it is reflecting for beams with the polarization of the transmitting beam, and permeable as free of losses as possible for beams with the polarization of the receiving beam. The fourth reflecting surface **R4** is formed by a dichroitic beam splitter **DBS**, for example. The fifth reflecting surface **R5** is formed by a fine pointing assembly **FPA** (Figs. 4 and 1). The quarter-wave plate **QWP1** converts the light of the transmitting channel, which had been linearly polarized up to now, into circularly polarized light for transmission through space to the partner terminal.

The receiving channel **Rx1** comprises, also viewed in the beam direction, the quarter-wave plate **QWP1**, the fifth reflecting surface **R5**, the dichroitic beam splitter **DBS**, the third reflecting surface **R3**, the reflecting beam splitter **PBS**, a focusing device **FR1** and the fiber nutator **5** or the receiving sensor **RS1**. The quarter-wave plate **QWP1** converts the

circularly polarized light from the partner terminal arriving from space into linearly polarized light.

The purpose of the beam splitter **PBS** is the differentiation between the transmitting and receiving beams. It is needed in the present exemplary embodiment or in cases, in which the transmitting and receiving beams differ by different polarization. In other exemplary embodiments, wherein the transmitting and receiving beams differ by different wavelengths, for example, a **DBS** would be used in place of a **PBS**.

The transmitting channel is used for transmitting data to the partner terminal, and the receiving channel for receiving data from the partner terminal, each one in an operational mode in which both terminals have already been roughly aligned with each other. The coarse pointing assembly **174** (**Fig. 1**, **CPA**) is used for rough alignment. It comprises on the one hand a light beacon, arranged at the partner terminal, for emitting a beacon light, and on the other hand the acquisition channel at the terminal for receiving the beacon light. The acquisition channel branches off the receiving channel **Rx** at the dichroitic splitter **DBS** and has a focusing device **FA** (**Fig. 4**) as well as the acquisition sensor **AS**. The detection range **AA** of the acquisition sensor **AS** is considerably greater than the detection range **RA** of the receiving sensor.

The arrangement in accordance with the invention operates as follows: the lightwave **1** comprises the communications beam, which transmits data, also called data light, and beacon light. The data light is tightly bundled and probably cannot hit the opposite station because of the "wobbling" resulting in the acquisition phase. The beacon beam is less bundled, which makes the permanent illumination of the opposite station possible. Thus, there is first the possibility to track the received beacon light with the acquisition sensor **171**. An attempt can be simultaneously made with the leak light to switch over to the nutator **5**. Since all this occurs during permanent illumination by the opposite station, no "twinkling" effect occurs, such as would occur if the communications beam were to be used. Thus there is time for locating the light spot, if the fiber nutator is not immediately acquired.

The lightwave received by the optical receiving unit **2**, **3** (**Fig. 1**), or from the elements **FPA**, **R4**, **R3**, **PBS** and **FR1** (**Fig. 4**) is approximately focused on the center of the monomode fiber **7** (**Fig. 1**) in the fiber nutator **5** (**Figs. 1, 4**) via the fine alignment unit **3** and with the aid of the lens **4**, or of the elements **PBS**, **FR1** (**Fig. 4**) when the control unit is inactive. When the control unit **14** (**Fig. 1**) is active, a movement (**Fig. 2**) of the fiber end **22** around the center of the monomode fiber **7** is caused by the fiber nutator **5**. The fiber end **22** preferably describes a high-frequency circular motion around the optical axis of the optical receiving device. Although the end of the fiber **7** is moved by the nutator, there is no longer a spatial movement of the exiting light at the end of the fiber, at the detectors **10** and **11**. Instead, the rotating movement by means of the nutator **5** causes an intensity modulation (**Fig. 3**) if the scanning motion does not take place exactly concentrically

around the light spot.

The high-frequency mechanical scanning movement of the fiber end caused by the nutator **5** (Figs. 1, 4), which in general can be a deflecting unit, can be controlled by means of a lateral displacement mechanism or by means of a bending element, for example. Rapid lateral displacement units with small movements are known, for example, from opto-electronic reading devices, such as CD players. But bending elements can be simply produced from small piezo-ceramic tubes with segmented electrodes. These small tubes are only fixed in place in one area, so that they can be bent in the linear direction by the piezo effect. It is common to all mechanisms that they are controlled by so-called I-Q signals. After I-Q demodulation of the intensity signal has taken place, the spatial error between the light spot **22** and the fiber axis is finally obtained. The error signals **Sm** and **Sn** (Fig. 1) cause the minimization of the deviation error via the system control **58**.

The relative offset between the intensity distribution of the Rx light in the focal plane of the lens **4** and the end of the fiber **7**, created by the rotary movement, therefore causes a chronologically asymmetric intensity signal on the detectors **10** and **11** if scanning of the fiber axis is not performed concentrically around the optical axis of the opto-mechanical system. Thus, the scanning point detector is replaced by the mode field of a monomode fiber, and this at a very good approximation. The scan radius should not exceed 1/10th of the mode field radius for preventing too large a signal decay of the light coupled into the fiber.

The lightwave guided over the chromatic diplexer **51** is divided into two almost identical partial beams by the beam splitter, which are fed to one of the respective detectors **10** and **11** after the light from the local laser **12** has been coupled into the light flow via the optical waveguide coupler **6**. Respectively two error portion signals are generated by the two detectors **10**, **11**, which are converted into voltages **Sa** or **Sb** by means of an appropriate front end transimpedance amplifier **15** or **16**. A spatial error signal is obtained from the signals **Sa** and **Sb**, which appears as the signal **Sn**( $\Delta x$ ,  $\Delta y$ ) at the output of the circuit **57** and is used for continuous tracking operations. By an addition of the error portion signals **Sa** and **Sb** having the correct signs, an output signal corresponding to the original data or communications signal results on the other side. A tracking sensor **TS**, which is present in such devices besides an acquisition sensor **AS** and a pointing sensor **173**, is therefore replaced by the invention.

The overlay of the local laser wave with the **Rx** wave takes place only in the glass fiber, so that the spatial correlation degree between the local laser and the **Rx** field will equal 1, i.e. an overlay guaranteed to be free of streaks takes place. It is then possible in connection with the optimization during adjustment, or a later optimization during operation, to assume an overlay guaranteed to be free of streaks, and an adjustment to the absolute amplitude maximum can be performed. This has been shown to be very advantageous compared with the free beam overlay wherein, in contrast to the method of

09740732.1-1800



the invention, it can happen that interference streaks caused by a tilt angle can occur when the two waves are overlaid on each other. It is then no longer possible to find the optimal, i.e. streak-free, adjustment state by means of the intensity maximum alone. Moreover, in that case the distance between the levels of the main maximum and one of the side maxima is relative short. There is always the latent danger that the tracking regulator will get out of step and perform a regulation in accordance with a side maximum of the intensity distribution, which then considerably limits the linear regulating range.

The uses of fiber nutation known so far require a coherent optical heterodyne reception. The reason for this is primarily the attainable good suppression of the effects of interference light. However, during the acquisition phase, in which an optical transmission path is being built up, there are no interfering natural light sources in the field covered by the acquisition sensors, so that in accordance with the invention the fiber nutators can also be employed already in the acquisition phase, although no heterodyne reception takes place.

Since fiber nutators have a selectively narrow field of coverage because of their monomode design, it is possible to achieve very high solid angle resolutions (sub-micro radians). Moreover, the beam of the beacon laser is not as tightly bundled as the communications beam, therefore it is possible to assure a permanent illumination of the opposite station already by using the wide angle camera.

During the acquisition phase the light from the beacon laser(s), which comes from high-output laser diodes, for example, is coupled into multimode fibers. The polarization state of the emitted light is therefore arbitrary. "High" losses therefore inherently occur on the receiving side (Fig. 4) during the chromatic splitting **R4** of the wavelengths of the beacon and communications light. The diplexers **R4** employed are optimized for low transmission losses of the communications light. Therefore, in respect to the beacon light, "cross talk" of the beacon wavelength into the communications channel always occurs, i.e. on the receiving end beacon light appears in the direction of the communications receiver. Thanks to the fiber front end which, in accordance with the invention is used according to the fiber nutation principle, there is the opportunity of also using the light leaked from the acquisition channel for the generation of tracking signals.

The acquisition sensor **171** and the coarse pointing assembly **174** operate in a manner known per se. Therefore there is the opportunity initially, or at the start, of tracking the received beacon light with the aid of the signal **Sc** wherein, as a replacement, a control loop via the elements **58**, **174**, **2**, **FPA**, **R4**, **171** is used for tracking which, because of the sensor **171**, has a slow control of band width, for example on the order of 50 Hz.

The signal **Sn** at the output of the discriminator **57** is basically used in the form of permanent tracking operations by the system control **58**. In this case an inner control loop operates, which is defined by the elements **57**, **58**, **175**, **3**, **51** and **5**. In addition an outer

control loop also operates, which is defined by the elements **58**, **174** and **2**. These control loops are very fast, because the sensors **10**, **11** and **53**, which quasi constitute point sensors with a glass fiber, can operate much faster than the sensor **171**. In contrast to this, the signal **Sm** at the output of the discriminator **57** is only used temporarily, namely only at the start, possibly within a maximum period of time of three minutes, for example. The system control **58** has means to determine whether the signals **Sc**, **Sm** and **Sn** are usable. Since the beacon light is received at a relatively wide angle, reception of the signal **Sc** is not problematical. This signal **Sc** is therefore used at the start until it is determined by the system control **58** whether the signal **Sm** is usable, i.e. whether or not the fiber nutator receives sufficient leaked light for generating tracking signals. From this moment on it operates with this signal **Sm**, wherein for reasons of reliability it is possible to continue running the sensor **171** in the acquisition phase. If thereafter it is determined by the system control **58** that the signal **Sn** is valid, or that the communication channel operates correctly, it takes over this signal **Sn** for a more accurate continuous tracking operation. It is possible at this time to switch off the signal **Sm** from the discriminator **56** by means of an enable signal **S6**, as well as to switch off the signal **Sc** no later than this time by means of an enable signal **S1**. These enable signals **S1** and **S6**, as well as a further enable signal **S7** for the discriminator **57**, are generated in the system control **58**, which needs the signals **Sc**, **Sm** and **Sn** at the same time for controlling the **CPA** and the **FPA**. But the control **14** always operates, for example with the aid of a clock generator.

The principle in accordance with the invention also applies to incoherent systems. Inherent system constructions or direct detection systems are sometimes produced in that the incoming light from the opposite station is focused onto a so-called avalanche diode. Inherently such systems are not monomode receivers, i.e. the receiver accepts light from a solid angle area which is greater than the solid angle area for limited diffraction systems described by diffraction theory. To minimize interfering background radiation, it is then necessary to employ optical filters with extremely narrow bandwidth. Up to now it has not been possible to produce such filters for long-term space travel applications.

Usually a separate tracking laser is used for tracking the opposite station. These lasers are distinguished by providing good wavelength stabilization. Again, optical filters with extremely narrow bandwidth (often so-called "atomic line filters") are placed in front of the receiver diode in the receiving station. The structural outlay for producing such systems can be significantly reduced by employing monomode receiver units. In the end this leads to savings regarding complexity, power requirements and mass. It is possible by using the monomode front end to return the spatial acceptance range of the receiver to the diffraction limits. This leads to a considerable reduction of the background radiation reaching the receiver. As a result, the demands made on the optical band pass filters used can be clearly reduced.

Moreover, by employing monomode receivers it is possible to reduce the scattered

light suppression (crossover into the transmitting channel) for the receiving channel to a significant degree. Suppression ranges of at least 50 dB can be achieved with this type of receiver, which could only be produced by means of band pass filters with considerably greater outlay. If it is possible to do without approximately 5% of the received output in the communications channel, the additional tracking system can be completely omitted. The use of a monomode receiver module in combination with a spatial search process, for example the fiber nutation principle, permits this realization. In Fig. 1, this situation is indicated by a possible additional connection between a further output of the fiber nutator 5 for a signal **Sw**, and of the unit in which the lens 4 is located for controlling it. This means that in accordance with the invention it is possible to use this additional output signal **Sw** of the fiber nutator 5 for the direct control of the FPA 3.

By means of using the receiving fiber 7, which can be relatively long, it is possible to house the receiver front end **RFE**, i.e. the detectors 10, 11 and the amplifiers 15, 16, at a relatively great distance from the optical devices. The lightwave fibers can be housed in a flexible protective cable for this purpose, or have a flexible sheathing. Thus the heat being generated at the **RFE** is optimally divorced from the optical devices and it is no longer necessary to fear thermal maladjustments in the optical sub-system induced by the **RFE**. Therefore the optical elements 2, 3, 4 and 5 can be arranged at a relatively large distance from the electronic data devices and the **RFE**, which are located in the remote electronics unit. Because of the mobility of portions of the fiber, it is therefore possible to remove all problems which result from the use of long microwave lines (damping, **EMC** [electromagnetic compatibility]), even if it is necessary to extend a coaxial line from the electronics unit to the optical head in order to send the low-frequency tracking error signals (**BW** = 10 kHz) back to the front.

Furthermore, the arrangement in accordance with the invention has been shown to be particularly advantageous in view of the fact that it has great long-term stability, that it can be optimized by means of a relatively simple algorithm in connection with beam overlay, that with high-frequency data flows (clock rate = 1000 Mbps) no particularly significant damping of the connecting line between the fiber nutator and the remote receiver front end **RFE** (cable length > 3 m) results, that it does not require any additional electronic line driver devices, that the cables need not be laid fixed in place, so that even movable partial areas are possible, that it is unproblematical in respect to **EMC** interferences, that **RFEs** with bandwidths >> 1 GHz can be used with broadband systems, and that a great heat generation from the HF electronic devices is avoided in the immediate vicinity of the optical devices. The arrangement in accordance with the present invention can in this way advantageously replace the elements 16 and 26 of the optical bench in accordance with the mentioned **EP 0 844 473 A1**.

With an embodiment of the invention, the system control 58 and/or the control 14 can be designed in such a way that a movement of the movable end of the lightwave fiber 7

around the center of the focusing point **22** of the information wave **1** is caused when the lens **4** is at rest.

With another embodiment of the invention, the system control **58** can cause a movement of the lens **4** in order to move the focused light spot **22** of the information wave **1** around the center of the lightwave fiber **7** when the lightwave fiber is at rest.

The arrangement in accordance with the present invention can be used for the same or similar purposes as those in the mentioned patent application **EP 0 831 604 A1**.

In such a system an optical traveling wave amplifier, for example an optical semiconductor amplifier, an erbium-doped fiber amplifier or an Nd- or Yb-doped fiber amplifier, can be provided in the transmitter. To suppress interfering background light, spatial filtering by means of optical monomode wave guides **6** can be provided.

The exemplary embodiments explained above are to be merely understood as means of illustrating the application of such an arrangement. However, other embodiments, which become immediately apparent to one skilled in the art from these, also contain the basic concept of the invention.